LIGHT TRACTION BATTERY (FLAT PLATE) 12V-230Ah


NX POWER DEEP CYCLE




MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND / MARQUE	NX Power Deep Cycle
TECHNOLOGY / TECHNOLOGIE	Flate Plate / Plaque plane
NOMINAL VOLTAGE / TENSION NOMINALE	12V
NOMINAL CAPACITY / CAPACITÉ NOMINALE	230Ah [20hrs]
	185Ah [5hrs]
DIMENSIONS / DIMENSIONS	
• Length / Longueur	518 mm
• Width / Largeur	273 mm
• Height / Hauteur	242 mm
• Total height with terminals / Hauteur totale (avec cosses)	242mm
WEIGHT / POIDS	
Acid included / Avec acide	58 kg
• Without acid / Sans acid	42 kg
POLARITY / POLARITÉ	- / +
TERMINAL / TYPE DE COSSES	Auto
CASING / TYPE DE BAC	Polypropylene (PP)
COLOR / COULEUR DE BAC	Black Top and White case









| 1/2

Leisure (nautical, caravan, camper...) / Loisir (marine, caravane..)

Electric traction (fork lift trucks and electric pallet trucks) / Semi traction (charriots élévateurs, transpalettes...)

APPLICATIONS / APPLICATIONS

TECHNICAL INFORMATION / INFORMATIONS TECHNIQUES

Industrial cleaning machines / Engins de nettoyage

GRIDS TECHNOLOGY / COMPOSITION DES GRILLES

SUGGESTED CHARGING CURRENT / COURANT DE CHARGE

OPERATING TEMPERATURE RANGE / PLAGE DE TEMPÉRATURE

STORAGE TEMPERATURE RANGE / TEMPERATURE DE STOCKAGE

FLOAT CHARGING VOLTAGE / TENSION DE CHARGE EN FLOATING

CYCLING CHARGING VOLTAGE / TENSION DE CHARGE EN CYCLAGE

MAX CYCLING / CYCLAGE MAX (80% DOD / 20°C)

Electric vehicles / Véhicules électriques

Lifting apparatus / Engins de levage

Lighting and solar / Energie solaire

www.enix-energies.com • Date: 2019/02/13

Pb - Sb

500

30A

-20°C / 45°C

-20°C / 40°C

13.5 - 13.8V

15.9 - 16.2


OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.




Part No: AMP1327

CHARGING PROFILE



LIFE CHARACTERISTICS OF CYCLIC USE





| 2/2

www.enix-energies.com • Date: 2019/02/13

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc, that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.